



Tourguide 2020-D L 2021-40 charger



FEATURES

- 40 bay charging unit for TourGuide 2020-D receivers
- Quick charging in less than 2,5 hours
- Easy configuration of the receivers by master/slave copy function
- Full software control (channel, language, volume settings)

The L 2021-40 charger rack has been specially designed for stationary applications. It holds up to 40 receivers that will automatically quick-charge to be ready for the next event. At the same time, the L 2021-40 serves as an ethernet interface to allow pre-selecting the active channel for each receiver on a central PC. Up to 125 charger racks with up to 5000 receivers can be connected to the PC. The CC 2021 control software offers simple presets to select and confirm channels for them all with just one click. Users and service staff can easily monitor which receivers at which station have been prepared for any given language or program. Configuration problems are a thing of the past!

ARTICLE INFORMATION

L 2021-40 Art. no. 502037

DELIVERY INCLUDES

- L 2021-40 charger
- Safety instructions

ACCESSORIES

EU mains cable Art. no. 054324
US mains cable Art. no. 054325
UK mains cable Art. no. 054327

SPECIFICATIONS

Mains socket	3-pin, protection class I, as per IEC/EN 60320-1
Mains voltage	100 to 240 V ~
Primary power consumption	max. 150 W
Charging voltage per charging compartment	typ. 5 V
Charging current per charging compartment	max. 400 mA
Charging time for HDE 2020-D	approx. 2.5 h
Charging time for EK 2020-D	approx. 5 h
Dimensions	approx. 483 x 399 x 172 mm
Weight (empty)	approx. 8.8 kg
Temperature range	+3 °C – +40 °C (38 °F - 104 °F)



Tourguide 2020-D L 2021-40 charger

DIMENSIONS

