



XS Wireless Digital INSTRUMENT RX

Model: RX Pedal

XS Wireless Digital INSTRUMENT RX receiver with 6.3 mm (1/4") plug. Designed to be used with a guitar amp, mixer or recording device with a 6.3 mm (1/4") input, this 2.4 GHz receiver will pair with any XSW-D transmitter. Offered as a replacement, this item includes a charging cable but does not include any other accessories.



FEATURES

- One touch ease-of-use
- 2.4 GHz digital transmission for worldwide operation
- 75 m range (250 ft) in optimal conditions
- Up to 5 hours battery life on a single charge
- Switch between multiple transmitters linked to one receiver

DELIVERY INCLUDES

- XSW-D INSTRUMENT RX (Model: RX Pedal)
- USB-C to USB-C charging cable
- Colored stickers for labelling
- Quick guide
- Safety guide

SPECIFICATIONS

USB C interface

Output voltage	5 V
Output current	typ. 380 mA
Input voltage	5 V
Current consumption	max. 185 mA

External power supply interface

Input voltage	9 - 15 V, typ. 12 V
Current consumption	max. 500 mA @ 9 V

AF characteristics

Codec	aptX® Live
Audio frequency response	10 - 18,000 Hz
Audio output	max. 12 dBu
Signal-to-noise ratio	≥ 106 dB
THD	< 0.1 %
Audio latency	< 4 ms

Product properties

Dimensions	approx. 130 x 82 x 51 mm
Weight	approx. 890 g
Frequency range	2,400 - 2,483.5 MHz
Modulation	GFSK with TDMA

Environmental conditions

Operating temperature	-10 °C to +55 °C (14 °F to 131 °F)
Relative humidity	95 % (non-condensing)



XS Wireless Digital INSTRUMENT RX

Model: RX Pedal

PRODUCT VARIANTS

XSW-D INSTRUMENT RX
Receiver with 6.3 mm (1/4") output
Art. no. 508498

AVAILABLE SETS

XSW-D VOCAL SET
XS 1 handheld, female XLR transmitter,
male XLR receiver
Art. no. 508484

XSW-D LAVALIER SET
ME2-II, 3.5 mm (1/8") transmitter, male
XLR receiver
Art. no. 508485

XSW-D PEDALBOARD SET
6.3 mm (1/4") transmitter, pedalboard
receiver
Art. no. 508486

XSW-D PORTABLE LAVALIER SETt
ME2-II, 3.5 mm (1/8") transmitter &
3.5 mm (1/8") receiver
Art. no. 508488

XSW-D PORTABLE INTERVIEW SET
Female XLR transmitter, 3.5 mm (1/8")
receiver
Art. no. 508489

XSW-D PORTABLE ENG SET
ME2-II, 3.5 mm (1/8") transmitter,
female XLR transmitter, 3.5 mm (1/8")
receiver
Art. no. 508490

XSW-D XLR BASE SET
Female XLR transmitter, male XLR
receiver
Art. no. 508491

XSW-D PRESENTATION BASE SET
3.5 mm (1/8") transmitter, male XLR
receiver
Art. no. 508492

XSW-D INSTRUMENT BASE SET
6.3 mm (1/4") transmitter, 6.3 mm
(1/4") receiver
Art. no. 508493

XSW-D PORTABLE BASE SET
3.5 mm (1/8") transmitter, 3.5 mm
(1/8") receiver
Art. no. 508621

ACCESSORIES

XSW-D XLR FEMALE TX
Transmitter with female XLR input
Art. no. 508494

XSW-D MINI JACK TX
Transmitter with 3.5 mm (1/8") input
Art. no. 508495

XSW-D INSTRUMENT TX
Transmitter with 6.3 mm (1/4") input
Art. no. 508496

XSW-D XLR MALE RX
Receiver with male XLR output
Art. no. 508497

XSW-D PEDALBOARD RX
Receiver with 6.3 mm (1/4") & male
XLR outputs
Art. no. 508499

XSW-D MINI JACK RX
Receiver with 3.5 mm (1/8") output
Art. no. 508500

NT XSW-D PEDALBOARD
Power supply for pedalboard receiver
Art. no. 508647

CL 35
3.5 mm (1/8") coiled output cable
Art. no. 508648

CI 63
6.3 mm (1/4") extension input cable
Art. no. 508649

XSW-D BELTPACK CLIP
Transmitter belt clip
Art. no. 508650

XSW-D HOTSHOE MOUNT
Camera mount for XSW-D receivers
Art. no. 508651



XS Wireless Digital INSTRUMENT RX

Model: RX Pedal

DIMENSIONS

XSW Digital RX Pedal

