

## Frequenzbereich / Frequency range / Bande de fréquence / Rango de frecuencias E 823 - 865 MHz

EBU TV channel

Ch. 65 (822-830 MHz)

Ch. 67 (838-846 MHz)

Ch. 69 (854-862 MHz)

ISM 863 – 865 MHz @10 mW

Ch. 66 (830-838 MHz)

Ch. 68 (846-854 MHz)

Ch. 70 (862-870 MHz)

Channel	Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	Bank 9	Bank 10	Bank 11	Bank 12	Bank 13	Bank 14	Bank 15	Bank 16	Bank 17	Bank 18	Bank 19	Bank 20	Bank U1 - U6	
1	863,125	854,900	863,100	838,100	840,050	838,250	838,850	838,475	824,000	824,050	824,100	824,150	824,200	824,250	824,300	823,100	830,100	838,100	846,100	854,100	freely selectable	
2	863,875	855,275	863,500	840,175	843,825	840,475	840,525	839,100	824,800	824,850	824,900	824,950	825,000	825,050	825,100	823,500	830,500	838,500	846,500	854,500		
3	864,250	855,900	864,100	848,750	844,950	844,575	841,200	840,350	826,000	826,050	826,100	826,150	826,200	826,250	826,300	824,100	831,300	839,300	847,300	855,300		
4	864,875	858,650	864,900	855,050	850,425	849,000	842,525	842,850	827,600	827,650	827,700	827,750	827,800	827,850	827,900	824,900	833,300	841,300	849,300	857,300		
5	824,000	860,400	854,100	856,175	852,250	849,725	849,950	846,100	836,400	836,450	836,500	836,550	836,600	836,650	836,700	826,100	833,900	841,900	849,900	857,900		
6	824,500	860,900	855,300	858,675	858,425	852,725	852,775	848,225	840,400	840,450	840,500	840,550	840,600	840,650	840,700	827,700	835,500	843,500	851,500	859,500		
7	829,500	861,750	858,500	861,900	859,250	860,150	858,225	852,225	844,800	844,850	844,900	844,950	845,000	845,050	845,100	829,900	836,900	844,900	852,900	860,900		
8	<b>832,125</b>	–	861,500	838,500	861,500	861,650	839,400	855,350	849,600	849,650	849,700	849,750	849,800	849,850	849,900	833,100	837,900	845,900	853,900	861,900		
9	<b>833,500</b>	–	854,600	840,750	838,100	838,700	845,050	856,725	855,600	855,650	855,700	855,750	855,800	855,850	855,900	835,500	825,300	823,300	823,100	823,100		
10	<b>837,250</b>	–	856,800	841,575	841,325	839,900	853,200	860,350	860,800	860,850	860,900	860,950	861,000	861,050	861,100	840,300	846,700	828,500	828,300	824,900		
11	<b>839,375</b>	–	860,600	847,750	859,825	841,825	859,100	838,100	863,200	863,250	863,300	863,350	863,400	863,450	863,500	844,300	851,100	850,700	830,100	829,300		
12	<b>842,125</b>	–	–	859,950	861,900	855,200	861,750	840,850	823,000	823,050	823,100	823,150	823,200	823,250	823,300	847,700	857,300	855,100	837,700	836,300		
13	<b>846,000</b>	–	–	853,400	846,600	843,450	859,625	841,975	823,400	823,450	823,500	823,550	823,600	823,650	823,700	855,300	863,100	863,100	860,100	843,500		
14	<b>856,375</b>	–	–	860,425	–	851,400	–	861,850	829,800	829,850	829,900	829,950	830,000	830,050	830,100	861,300	864,900	864,900	864,900	849,300		
15	<b>857,875</b>	–	–	–	–	854,300	–	850,900	833,000	833,050	833,100	833,150	833,200	833,250	833,300	828,400	831,800	839,800	847,800	855,800		
16	<b>860,750</b>	–	–	–	–	–	–	852,625	834,300	834,350	834,400	834,450	834,500	834,550	834,600	851,600	842,800	857,600	824,200	832,200		
	ISM & UK Fixed Site License required by all users	UK Channel 69 Shared License required	ISM & Nordic Fixed Site License required by all users	Germany User Group a	Germany User Group b	Germany User Group c	Germany User Group d	Germany User Group e Indoors	Full range (1)	Full range (2)	Full range (3)	Full range (4)	Full range (5)	Full range (6)	Full range (7)	EU TV-Channel 65 & more	EU TV-Channel 66 & more	EU TV-Channel 67 & more	EU TV-Channel 68 & more	EU TV-Channel 69 & more		

FR

Les émetteurs et les récepteurs sont disponibles dans une plage de fréquences UHF de 42 MHz de largeur, ce qui autorise un choix parmi 1680 fréquences d’émission et de réception.

Les émetteurs et les récepteurs possèdent 26 banques de fréquences avec respectivement jusqu’à 16 canaux.

Chacun des canaux dans les banques de fréquences « 1 » à « 20 » (banques système) est assigné une fréquence fixe et préréglée (preset) en usine. Les fréquences préréglées au sein d’une banque de fréquence sont compatibles entre elles, c.à.d. exemptes d’intermodulation. Elles ne peuvent pas être modifiées.

Les banques de fréquences « U1 » – « U6 » (banques utilisateur) permettent de mémoriser des fréquences au choix, qui peuvent être réglées par pas de 25 kHz. Il se peut que ces fréquences ne soient pas exemptes d’intermodulation.

Le tableau figurant dans les pages intérieures dresse la liste des fréquences préréglées dans les banques de fréquences « 1 » à « 20 ».

- i**

Il est indispensable d’observer les indications figurant dans le supplément d’information sur la puissance HF.
- i**

Veillez à utiliser des fréquences autorisées dans votre pays. Si nécessaire, demandez une licence d’émission auprès de l’autorité correspondante.

Les paramètres par défaut suivants, préréglés en usine, peuvent être restaurés à tout moment via l’option « Reset » :

Auto Lock	inactive
Squelch (EK)	5 dB
Sensitivity (SR)	-18 dB
RF Power (SR)	Standard
Limiter (EK)	activo; -6 dB
Mode	<b>Stereo</b>
Ballance (EK)	<b>0</b>
<b>High Boost (EK)</b>	<b>flat</b>
Pilot Tone	n’est pas réinitialisé
User Banks “U”	n’est pas réinitialisé
Sync Settings (SR)	inactif
fWarnings (SR)	activ
IP Address (SR)	auto-IP

ES

Para la transmisión se dispone de un rango de frecuencia de hasta 42 MHz de amplitud con hasta 1680 frecuencias de transmisión/recepción en la banda UHF.

Los transmisores y los receptores disponen cada uno de 26 bancos de canales con hasta 16 canales.

En los bancos de canales «1» a «20» (bancos de sistema) se han ajustado de fábrica preajustes de frecuencia (frecuencias fijas). Dentro de un banco de sistema, los preajustes de frecuencia se encuen­tran libres de intermodulación entre ellos. Estos no se pueden cambiar.

En los bancos de canales «U1»–«U6» (bancos de usuario) puede ajustar libremente y guardar frecuencias a pasos de 25 kHz. Estas frecuencias pueden no estar libres de intermodulación.

Los preajustes de frecuencia en los bancos de canales «1» a «20» se representan en la tabla que se encuentra en las páginas interiores.

- i**

Il est indispensable d’observer les indications figurant dans le supplément d’information sur la puissance HF.
- i**

Veillez à utiliser des fréquences autorisées dans votre pays. Si nécessaire, demandez une licence d’émission auprès de l’autorité correspondante.

El símbolo de información (i) indica que se debe leer el suplemento de información sobre la potencia de RF.

Con la opción de menú «Reset», se pueden llamar de nuevo los siguientes ajustes de fábrica en todo momento:

Auto Lock	inactive
Squelch (EK)	5 dB
Sensitivity (SR)	-18 dB
RF Power (SR)	Standard
Limiter (EK)	activo; -6 dB
Mode	<b>Stereo</b>
Ballance (EK)	<b>0</b>
<b>High Boost (EK)</b>	<b>flat</b>
Pilot Tone	no se resetea con Reset
User Banks “U”	no se resetea con Reset
Sync Settings (SR)	inactivo
Warnings (SR)	activo
IP Address (SR)	auto-IP

DE

Für die Übertragung steht im UHF-Band ein 42 MHz breiter Frequenzbereich mit 1.680 möglichen Sende-/Empfangsfrequenzen zur Verfügung.

Die Sender und Empfänger verfügen über jeweils 26 Kanalbänke mit bis zu 16 Kanälen.

In den Kanalbänken „1“ bis „20“ (Systembänke) sind werkseitig Frequenz-Presets (feststehende Frequenzen voreingestellt. Innerhalb einer Kanal-bank sind die Frequenz-Presets untereinander intermodulationsfrei. Sie sind nicht veränderbar.

In den Kanalbänken „U1“ bis „U6“ (User Banks) können Sie in 25-kHz-Schritten Frequenzen frei einstellen und abspeichern. Diese sind unter Um­ständen nicht intermodulationsfrei.

Die Frequenz-Presets in den Kanalbänken „1“ bis „20“ sind in der Tabelle auf den innenseiten dargestellt.

- i**

Beachten Sie unbedingt die Angaben im HF-Leistungsbeiblatt!
- i**

Stellen Sie sicher, dass die gewünschten Frequenzen in Ihrem Land zugelassen sind und beantragen Sie ggf. eine Betriebs­erlaubnis

Das Informations-Symbol (i) zeigt an, dass Sie das HF-Leistungsbeiblatt lesen müssen.

Folgende Werkseinstellungen sind mit dem Menüpunkt **Reset** jederzeit wieder abrufbar.

Auto Lock	inaktiv
Squelch (EK)	5 dB
Sensitivity (SR)	-18 dB
RF Power (SR)	Standard
Limiter (EK)	aktiv; -6 dB
Mode	<b>Stereo</b>
Ballance (EK)	<b>0</b>
<b>High Boost (EK)</b>	<b>flat</b>
Pilot Tone	wird nicht zurückgesetzt
User Banks “U”	wird nicht zurückgesetzt
Sync Settings (SR)	inaktiv
Warnings (SR)	aktiv
IP Address (SR)	auto-IP

EN

Transmitters and receivers are available in a 42 MHz UHF frequency range with a total of 1,680 transmission/receiving frequencies.

Transmitters and receivers have 26 frequency banks with up to 16 channels each.

Each of the channels in the frequency banks “1” to “20” (system banks) has been factory-preset to a fixed frequency (frequency preset). The frequency presets within one frequency bank are intermodulation-free. These frequencies cannot be changed.

The frequency banks “U1”–“U6” (user banks) allow the user to store individual frequencies which are freely selectable in 25-kHz steps. It might be that these frequencies are not intermodulation-free.

The table on the inner pages lists the frequency presets in the frequency banks “1” to “20”.

The information symbol (i) indicates that you must read the RF power information sheet.

- i**

It is vital to observe the indications given on the RF power information sheet.
- i**

Make sure that the desired frequencies are approved and legal in your country and, if necessary, apply for an operating license.

The information symbol (i) indicates that you must read the RF power information sheet.

The following factory-preset default settings can be recalled any time via the **Reset** menu item.

Auto Lock	inactive
Squelch (EK)	5 dB
Sensitivity (SR)	-18 dB
RF Power (SR)	standard
Limiter (EK)	active; -6 dB
Mode	<b>Stereo</b>
Ballance (EK)	<b>0</b>
<b>High Boost (EK)</b>	<b>flat</b>
Pilot Tone	will not be reset
User Banks “U”	will not be reset
Sync Settings (SR)	inactive
Warnings (SR)	active
IP Address (SR)	auto-IP

Additional information for Sennheiser evolution wireless 300 IEM G3 systems

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3

Additional information for Sennheiser evolution wireless ew 300 IEM G3