

SENNHEISER



**Frequenzbereich / Frequency range /
Bande de fréquence / Rango de frecuencias**

**E 821 – 832 MHz
863 – 865 MHz**

Sennheiser electronic GmbH & Co. KG

Am Labor 1, 30900 Wedemark, Germany, www.sennheiser.com
Printed in Taiwan, Publ. 02/17, 571321/A02

E 821 – 832 / 863 – 865 MHz

EBU TV channel	Ch. 64 (814-822 MHz)	Ch. 65 (822-830 MHz)	Ch. 66 (830-838 MHz)
	ISM band (863-865 MHz)	Duplex gap (823-832 MHz)	

Channel		Bank 1	Bank 2	Bank 3	Bank 4	Bank 5	Bank 6	Bank 7	Bank 8	
XS WIRELESS 2 **	XS WIRELESS 1 *	1	863.100	863.100	863.200	863.150	863.150	863.100	863.250	863.250
		2	863.500	863.500	863.700	863.550	863.950	863.700	863.650	863.850
		3	864.300	864.000	864.100	864.050	864.450	864.500	864.150	864.350
		4	864.900	864.800	864.800	864.850	864.850	864.900	864.750	864.750
		5	823.100	823.100	823.200	823.150	823.100	823.100	823.150	823.250
		6	823.500	823.700	823.800	823.750	823.700	823.600	823.850	823.950
		7	824.100	824.700	824.600	824.750	824.700	824.600	824.850	824.950
		8	825.500	825.800	825.600	825.850	825.800	825.300	825.650	825.750
		9	826.300	826.500	826.800	826.550	826.500	826.200	826.850	826.950
	0* / 10**	828.900	827.700	828.100	827.750	827.700	827.300	828.250	828.350	
		11	830.100	829.100	829.600	829.150	829.100	829.200	829.550	829.650
		12	831.900	830.600	831.300	831.650	830.600	831.600	831.150	831.250



Informieren Sie sich bei Ihrer zuständigen Zulassungsbehörde über die erlaubten Sendefrequenzen, Sendeleistungen und beantragen eine Betriebserlaubnis für diese Funkanlage.

Please contact your radio licensing authority in your country, who will advise you on the available frequencies and transmitter power requirements.